

# DIA 8500 EBWH-T



Life Goes On...



## GENERATOR

Type	Three-Phase
Voltage Regulate	Automatic Voltage Regulator-AVR
Frequency(Hz)	50
Rated AC Voltage(V)	220/380
Rated AC Output(KVA)	7.5 kVA
Peak AC Output(KVA)	8 kVA
Power Factor	COSφ = 0,8

## ENGINE

Model	Briggs & Stratton
Type	OHV Forced Air-Cooled 4-Stroke
Bore x Stroke (mm)	90 x 66
Displacement(ml)	420
Max. output(HP/rpm)	15.0 / 3600
Fuel	Unleaded Gasoline
Fuel Tank Capacity(L/gal)	25
Continuous Operating Hours h	8
Oil	SF or Higher Grade
Ignition system	T.C.I.
Starting System	Electric Start
Operating Noise Leve(7m)dB(A)	72

## STANDARD FEATURES

Fuel Gauge	√
Engine Switch	√
Voltmeter	√
AC circuit Breaker	√
AC Socket	√
Pilot Light	√
Wheel&Handle	4 x 8"
Battery(for E-start)	18Ah
Hours Meter	-
DC Output	√
DC Circuit Breaker	√

## PACKAGE DIMENSIONS

DimensionsLxWxH(mm)	790 x 550 x 602
Gross Weight(kgs)	104
Net Weight(kgs)	100